

---

## INTRODUCTION

### 2X2 4K VIDEO WALL CONTROLLER:

The 4K 2x2 video wall controller , support 1-way HDMI or DVI input and 4 HDMI output, the main function is to divide a complete HDMI,DVI HD image signal into 4 blocks and assign to 4 video display unit (such as Rear projection unit, LCD TV, etc.), Complete with 4 HDMI high-definition video display units to form a large dynamic image screen.




### Multiple splicing modes



1x1



1x2



## FEATURES

Support 1 DVI or HDMI input

Input support HDMI1.4 ,HDCP1.4

Support 4 HDMI outputs, 1 3.5mm audio output

Input resolution include 1920x1080P 25/30/50/60HZ,3840x2160P 25/30HZ; Output resolution include 1920x1080P 25/30/50/60HZ



Input format: YUV422 16bit、RGB444 24bit; Output format: RGB444 24bit

Support RS232 protocol (Net port RJ45)

Easy to operate, plug and play

DC12V/2A power adapter

## Physical interface diagram





- 1: OFF/ON --- OFF/ON
- 2: HDMI IN ---HDMI input
- 3: HDMI input signal indicator
- 4: DVI IN --- DVI input
- 5: DVI input signal indicator
- 6: L/R OUT -- 3.5mm Stereo output
- 7: SWITCH --- SWITCH
- 8: IR --- Infrared receiver
- 9: RS232 --- RS232 port
- 10: HDMI output signal indicator
- 11-14: OUT PUT1-OUT PUT4 port
- 15: DC/12V ---DC12V Power Interface

## The instruction of remote control button:




- : Input switching selection
- : Brightness adjustment
- : Contrast adjustment
- : Sharpness adjustment
- : Chroma adjustment
- : Tint (green/red) adjustment
- : Output 180°Flip
- : Bezel compensation
- : Mode selection


# Operating and Connecting



Top-Left---OUTPUT1; Top-Right---OUTPUT2  
 Botom-Left---OUTPUT3; Botom-Right---OUTPUT4



Left---OUTPUT1/OUTPUT3  
 Right---OUTPUT2/OUTPUT4



First---OUTPUT1; Second---OUTPUT2  
 Third---OUTPUT3; Fourth---OUTPUT4

## The Package includes:

- 1. 4K 2X2 video wall controller x1
- 2. Power adapter x1
- 3. User Manual x1